Honeywell



- : not avaliable on camera

*1: not avaliable on software

*2: not test on software

For multi stream support:

Yes: multi stream fix to 500kbps/100kbps Yes*: multi stream setting support

| | | | | res i man | . ou ca | II octi | .g .u | pport | | | | |
|----------------|---|-----------------|-------------|-------------------|---------|-----------|-------|-----------------------|------|----------------------------|----------|---------------------|
| Device Name | Tested Firmware | Video Format | Video Ch | Max Resolution | Audio | I/O Ch | PTZ | On- Edge Motion | UPnP | Multi Stream Support | Snapshot | Remarks |
| ACUIX | 1.5.6 | MPEG4 | 1 | 4CIF | - | - | Yes | - | - | Yes | - | |
| Note: | Sometimes the PTZ function doesn't work properly due to camera FW; users have to restart to make it work. The speed of PTZ is not correspondent with camera web, which might be due to camera FW. | | | | | | | | | | | |
| H3D1F | 40.0.6 | H.264 | 1 | 1280x720 | 1-way | 1/0 | - | Yes | - | Yes | - | |
| Note: | To ensure compatibility with H3D1F1, H3D1F2, H3D1F3, H4D1F1, HCD1F, HCW1F, H3W1F1, H4W1F1, H3D1F2X, H3D1F3X, H4D1F1X, HCD1FX, HCW1FX, H3W1F1X or H4W1F1X, H3D1F must be selected to work with either model. | | | | | | | | | | | |
| H3D2F | 40.0.6 | H.264 | 1 | 1920x1080 | 1-way | 1/0 | Yes | Yes | - | Yes | - | |
| Note: | 1. H3D2F: Only support Zoom, not supprot Pan and Tilt. 2. To ensure compatibility with H3D2F1X, H3D2F1, H4D2F1 or H4D2F1X, H3D2F must be selected to work with either model. | | | | | | | | | | | |
| HCD554IP | 5.4.5 | MPEG4 | 1 | 4CIF | 1-way | 0/1 | - | - | - | Yes | - | |
| Note: | Disable input function due to camera FW. | | | | | | | | | | | |
| НСФ5МІН□ | 13.1.2 | Н.264 | 1 | 1280x720 | 1-way | 1/1 | - | Yes | - | - | - | |
| Note: | For integration issue not support TCP connection. | | | | | | | | | | | |
| HD3MDIH | 11.0.3 | H.264 | 1 | 1280x720 | 1-way | 1/1 | - | Yes | - | - | - | |
| Note: | For integration issue not support TCP connection. | | | | | | | | | | | |
| HD3MDIP | 7.07 | MPEG4 | 1 | 1280x720 | 1-way | - | - | Yes | - | Yes | - | |
| HD4MDIP | 8.04 | MPEG4 | 1 | 1280x720 | 1-way | - | - | Yes | - | Yes | - | |
| HD4MDIH | 12.0.3 | H.264 | 1 | 1280x720 | 1-way | 1/1 | - | Yes | - | - | - | |
| Note: | For integration issue not support TCP connection. | | | | | | | | | | | |
| HNVE1 | 6.3.4 | MPEG4 | 1 | 4CIF | 1-way | - | - | - | - | Yes | - | |
| Note: | Disable I/O function due to camera FW. | | | | | | | | | | | |
| HDZ20HDX | H20120808N SA | H.264 MJPEG | 1 | 1920x1080 | 1-way | 4/2 | Yes | Yes | Yes | Yes | Yes | |
| HDZ20HDE X | | H.264 MJPEG | 1 | 1920x1080 | 1-way | 4/2 | Yes | Yes | Yes | Yes | Yes | Supported by design |

Honeywell



- : not avaliable on camera

*1: not avaliable on software

*2: not test on software

For multi stream support:

Yes: multi stream fix to 500kbps/100kbps Yes*: multi stream setting support

| Device Name | Tested Firmware | Video Format | Video Ch | Max Resolution | Audio | I/O Ch | PTZ | On- Edge Motion | UPnP | Multi Stream Support | Snapshot | Remarks |
|----------------|--|-----------------|-------------|-------------------|-------|-----------|-----|-----------------------|------|----------------------------|----------|---------------------|
| HDZ20HD | Refer to HDZ20HDX(H 20120809NS | H.264 MJPEG | 1 | 1920x1080 | 1-way | 4/2 | Yes | Yes | Yes | Yes | Yes | Supported by design |
| HDZ20HDE | Refer to HDZ20HDX(H 20120810NS A) | | 1 | 1920x1080 | 1-way | 4/2 | Yes | Yes | Yes | Yes | Yes | Supported by design |
| Note: | Parameter setting will fail when Mjpeg quality bigger than 60 | | | | | | | | | | | |
| Note: | HD3MDIP, HD4MDIP: Not support I/O currently. All models: Users may be confused because the username on login page of camera web is "administrator", but it's "admin" actually. If you type in "administrator", you are no longer to connect the cameras. | | | | | | | | | | | |
| Note | One of the cameras in the system must support I/O functions in order to enable the snapshot feature. This is a known issue and we are looking to fix it with the next product version update. | | | | | | | | | | | |